



Interconnector – Pars TU5 ECO MUX

1501052

Rear				IC23A 16W BK	Instrument Panel			
Part	Connector	Pin Num	Wire Num	Interconnector Pin Num	Wire Num	Pin Num	Connector	Part
BF00A	8W BK	E1	A241	1	A241	2	2W WI	3110
RB00B	10W WI	A1						
RB00B	10W WI	B1						
IC23C	36W BK	33						
BCMA	40W BK	2				7	8W BK	8410A
2100	2W WI	2						
8406	1W RD	1						
3065	2W BR	1						
BF00A	8W BK	E3	C221	2	C06	25	40W GY	8025
						5	50W OR	6570
BCMB	15W WI	A7	V276	3	V276	6	8W BK	8410A
IC23C	36W BK	8				6	18W BK	8025A
IC22B	16W BK	10				35	40W GY	8025
IC33	12W WI	1				1	1W BK	3053
2635	6W BR	1				A3	13W BK	IC24A
2630	6W BR	6						
IC32	12W WI	1						
2633	2W BK	2					6	8W WI
BCMA	40W BK	1	475B	4	475B	12	50W OR	6570
4730	2W WI	2	475					
BCMA	40W BK	37	623B	5	623B	21	50W OR	6570
BCMA	40W BK	35	8116	6	8116	39	40W GY	8025
BCMA	40W BK	29	8038	7	8038A	B1	13W GY	IC26B
						38	40W GY	8025
RB00B	10W WI	A3	8031	8	803	A1	13W BK	IC26A
						B7	13W BK	IC26A
						3	6W BK	8031
BF00A	8W BK	E2	A23	9	A23	1	3W BK	8100
BCMA	40W BK	30	629	10	629	2	18W BK	8025A
BCMA	40W BK	36	622	11	622	17	18W BK	8025A
BCMA	40W BK	17	623	12	V622	16	18W BK	8025A
BCMA	40W BK	15	230	13	230	9	18W BK	8025A
BCMA	40W BK	18	230B	14	230B	11	18W BK	8025A
IC22B	16W BK	13	612	15	612	13	18W BK	8025A
BF00B	8W WI	E4	B25	16	B28	4	8W BK	8410A
						26	40W GY	8025
						4	18W BK	8025A

Rear				IC23B 16W GN	Instrument Panel			
Part	Connector	Pin Num	Wire Num	Interconnector Pin Num	Wire Num	Pin Num	Connector	Part
BCMD	15W BK	B2	6061	1	6061	A5	13W BK	IC24A
BCMD	15W BK	A2	6062	2	6062	A1	13W BK	IC24A
IC23C	36W BK	10	2344	3	2344	B1	13W GY	IC24B
2635	6W BR	5						
BCMB	15W WI	A9						
BCMA	40W BK	10	3052	4	3052	B2	13W BK	IC24A
BCMA	40W BK	8	6252	5	6252	B6	13W BK	IC24A
BCMB	15W WI	B2	6211	6	6211	B1	13W BK	IC24A
IC22B	16W BK	4						
6265	2W WI	1						
IC32	12W WI	9						
IC33	12W WI	9						
IC22B	16W BK	16	6405	7	6405	B3	13W GY	IC24B
IC22B	16W BK	15	6406	8	6406	B4	13W GY	IC24B
BCMD	15W BK	B3	6071	9	6071	A6	13W BK	IC24A
BCMD	15W BK	A4	6072	10	6072	A2	13W BK	IC24A
IC23C	36W BK	35	252	11	252	3	8W WI	IC20
IC22A	16W GN	10	6411	12	6411	A5	13W GY	IC24B
IC22A	16W GN	11	6412	13	6412	A6	13W GY	IC24B
IC22A	16W GN	14	641	14	641	A3	13W GY	IC24B
BCMB	15W WI	B3	6201	15	6201	B4	13W BK	IC24A
IC22B	16W BK	6						
6265	2W WI	2						
IC32	12W WI	7						
IC33	12W WI	7						
Not Used								



Interconnector – Pars TU5 ECO MUX

1501052

Rear				IC23C 36W BK		Main										
Part	Connector	Pin Num	Wire Num	Interconnector Pin Num	Wire Num	Pin Num	Connector	Part								
BF00A	8W BK	S2	AA01	1	AA01	1	2W GY	SW00B								
BF00A	8W BK	S4														
BF00A	8W BK	S1														
BF00A	8W BK	S3	CC4	2	CC4	2	2W GY	SW00B								
						B1	10W GY	RB003								
						S2	8W BK	BF00D								
						S3	8W BK	BF00D								
7015	2W BK	2	703	3	703	32	38W BK	7020								
7015	2W BK	1	7031	4	7031	19	38W BK	7020								
7010	2W BK	2	702	5	702	20	38W BK	7020								
7010	2W BK	1	7021	6	7021	33	38W BK	7020								
4310	6W BK	3	121	7	121	3	10W GY	IC02A								
BCMB	15W WI	A7	V275	8	V275	9	16W BK	IC01								
IC23A	16W BK	3														
IC22B	16W BK	10														
IC33	12W WI	1														
2635	6W BR	1														
2630	6W BR	6														
IC32	12W WI	1														
2633	2W BK	2														
BCMB	15W WI	A8														
IC22B	16W BK	12	2333B	9	2331	4	16W BK	IC01								
2630	6W BR	2				1	2W BR	2340								
BCMB	15W BK	A9	2343B	10	2341	1	2W BR	2345								
IC23B	16W GN	3				10	16W BK	IC01								
2635	6W BR	5				10	16W BK	IC01								
BCMA	40W BK	21	9020	11	9020	5	8W BK	8208								
						6	16W BK	C001								
						4	10W BK	IC02B								
						14	38W BK	7020								
BCMA	40W BK	22	9019	12	9019	6	8W BK	8208								
						14	16W BK	C001								
						3	10W BK	IC02B								
						2	38W BK	7020								
4310	6W BK	1	430	13	430	7	10W BK	IC02B								
4310	6W BK	6	431	14	431	8	10W BK	IC02B								
1215A	2W BR	2	184	15	184	10	10W BK	IC02B								
IC23D	16W GY	14	6561	16	6561	11	18W WI	ICN								
IC23D	16W GY	15	6560	17	6560	12	18W WI	ICN								
BCMA	40W BK	12	210A	18	2103	16	38W BK	7020								
2111	2W BR	2														
2110	2W WI	2														
2100	2W WI	1														
IC23D	16W GY	13	6220	19	6220	13	16W BK	C001								
IC23D	16W GY	10	832	20	832	3	16W BK	IC01								
BCMB	15W WI	A5	VE04	21	VE04	18	18W WI	ICN								
3010	3W BR	2														
3020	3W BR	2														
IC23D	16W GY	7														
D03A		1														
IC22B	16W BK	9														
IC23D	16W GY	8	403	22	403	5	10W GY	IC02A								
IC220	8W WI	3	2207	23	2207	2	5W WI	2225								
BF00C	8W BK	S1	B09	24	BB0D	S1	8W BK	BF001								
						S2	8W BK	BF001								
						S3	8W BK	BF001								
						S4	8W BK	BF001								
						S1	8W WI	BF002								
BF00C	8W BK	S2				S2	8W WI	BF002								
						S3	8W WI	BF002								
						S4	8W WI	BF002								
						S1	8W BK	BF003								
						S2	8W BK	BF003								
						S3	8W BK	BF003								
						BB00A										
BF00B	8W WI	S4	B03	25	B03	E2	8W BK	BF001								
BF00C	8W BK	S3														
BF00C	8W BK	S4														
1215A	2W BR	1	183	26	183	9	10W BK	IC02B								
BCMA	40W BK	39	234	27	234	A2	10W BK	0002								
BCMA	40W BK	40	233	28	233	A4	10W BK	0002								
BCMA	40W BK	26	505	29	505	B1	11W GY	0005								
BCMA	40W BK	27	511	30	511	B2	11W GY	0005								
BCMB	15W WI	A4	2206	31	2206	1	5W WI	2225								
2635	6W BR	4														
2630	6W BR	3														
IC220	8W WI	1														
BCMA	40W BK	24	253	32	253	A2	10W BK	RB001								
BF00A	8W BK	E1	A243	33	A243	B6	15W WI	FCMB								
RB00B	10W WI	A1														
RB00B	10W WI	B1														
IC23A	16W BK	1														
BCMA	40W BK	2														
2100	2W WI	2														
8406	1W RD	1				14	18W WI	ICN								
3065	2W BR	1														
IC23D	16W YG	9	1810	34	1810											
IC23B	16W GN	11	252	35	252A											
BF00B	8W WI	S1	B04	36	B04											
BF00B	8W WI	S2			E1	8W BK	BF001									
BF00B	8W WI	S3														



Interconnector – Pars TU5 ECO MUX

1501052

Rear				IC23C 16W GN		Main			
اگر دسته سیم داخل اتاق YG22241806 و دسته سیم اصلی YG22241807 بود									
Part	Connector	Pin Num	Wire Num	Interconnector Pin Num		Wire Num	Pin Num	Connector	Part
BF00A	8W BK	S2	AA01	1	AA01	1	2W GY	SW00B	
BF00A	8W BK	S4							
BF00A	8W BK	S1							
BF00A	8W BK	S3	CC4	2	CC4	2	2W GY	SW00B	
						B1	10W GY	RB003	
						S2	8W BK	BF00D	
						S3	8W BK	BF00D	
7015	2W BK	2	703	3	703	32	38W BK	7020	
7015	2W BK	1	7031	4	7031	19	38W BK	7020	
7010	2W BK	2	702	5	702	20	38W BK	7020	
7010	2W BK	1	7021	6	7021	33	38W BK	7020	
4310	6W BK	3	121	7	121	3	10W GY	IC02A	
BF00C	8W BK	S1	B09	8	BB0D	1	1W	BB00A	
						S1	8W BK	BF001	
						S2	8W BK	BF001	
						S3	8W BK	BF001	
						S4	8W BK	BF001	
BF00C	8W BK	S2				S1	8W WI	BF002	
						S2	8W WI	BF002	
						S3	8W WI	BF002	
						S4	8W WI	BF002	
						S1	8W BK	BF003	
						S2	8W BK	BF003	
						S3	8W BK	BF003	
BF00C	8W BK	S3				B03	9	B03	E2
BF00C	8W BK	S4							
BF00B	8W W1	S4							
BCMB	15W W1	A7	V275	10	V275	9	16W BK	IC01	
IC23A	16W BK	3							
IC22B	16W BK	10							
IC33	12W W1	1							
2635	6W BR	1							
2630	6W BR	6							
IC32	12W W1	1							
2633	2W BK	2							
2636	2W BK	2							
BCMB	15W W1	A8							
IC22B	16W BK	12	2333B	11	2331	1	2W BR	2340	
2630	6W BR	2	2343B	12	2341	4	16W BK	IC01	
BCMB	15W W1	A9				1	2W BR	2345	
2635	6W BR	5				10	16W BK	IC01	
IC23B	16W GN	3							
BCMA	40W BK	21	9020	13	9020	5	8W BK	8208	
						6	16W BK	C001	
						14	38W BK	7020	
						4	10W BK	IC02B	
BCMA	40W BK	22	9019	14	9019	6	8W BK	8208	
						14	16W BK	C001	
						2	38W BK	7020	
						3	10W BK	IC02B	
4310	6W BK	1	430	15	430	7	10W BK	IC02B	
BF00B	8W W1	S1	B04	16	B04	E1	8W BK	BF001	
BF00B	8W W1	S2							
BF00B	8W W1	S3							

Drawn by: Engineering Dep. of ISACO

2015.07.07



Interconnector – Pars TU5 ECO MUX

1501052

Rear				IC23D 16W GY	Instrument Panel			
Part	Connector	Pin Num	Wire Num	Interconnector Pin Num	Wire Num	Pin Num	Connector	Part
RB00B	10W WI	B5	814	1	814	B2	13W GY	IC24B
IC22B	16W BK	1						
8120A	1W BK	1						
IC22A	16W GN	15						
8430	2W WI	1	6120	2	6120	12	18W BK	8025A
8430	2W WI	2	846	3	846	8	8W WI	8410B
8435	2W WI	2	845	4	845	7	8W WI	8410B
8435	2W WI	2	847	5	847	1	8W WI	8410B
8435	2W WI	1	848	6	848	2	8W WI	8410B
BCMB	15W WI	A5	VE05	7	VE05	B3	13W BK	IC24A
3010	3W BR	2						
3020	3W BR	2						
IC23C	36W BK	21						
D03A		1						
IC22B	16W BK	9						
IC23C	36W BK	22	403	8	403	11	40W GY	8025
IC23C	36W BK	34	1810	9	1810	1	18W BK	8025A
IC23C	36W BK	20	832	10	832	12	40W GY	8025
IC22A	16W GN	12	841	11	8411	2	3W BK	8440
IC22A	16W GN	13	842	12	841	5	8W WI	8410B
					8421	1	3W BK	8440
					842	6	8W WI	8410B
					6220	9	50W OR	6570
IC23C	36W BK	19	6220	13	6220	9	50W OR	6570
IC23C	36W BK	16	6561	14	6561	8	50W OR	6570
IC23C	36W BK	17	6560	15	6560	7	50W OR	6570
Not Used				16	Not Used			

Instrument panel				IC24A 13W BK	Front Door RH			
Part	Connector	Pin Num	Wire Num	Interconnector Pin Num	Wire Num	Pin Num	Connector	Part
IC23B	16W GN	2	6062	A1	6062	1	6W BK	6005
IC23B	16W GN	10	6072	A2	6072	2	6W BK	6005
8410A	8W BK	6	V27D	A3	V27D	5	6W BK	6005
8025A	18W BK	6						
8025	40W GY	35						
3053	1W BK	1						
IC23A	16W BK	3						
IC20	8W WI	6						
IC23B	16W GN	1	6061	A5	6061	2	2W GY	6045
IC23B	16W GN	9	6071	A6	6071	1	2W GY	6045
Not Used				A7	Not Used			
IC23B	16W GN	6	6211	B1	621A	2	2W BR	6245
IC23B	16W GN	4	3052	B2	3052	1	2W GY	3001
IC23D	16W GY	7	VE05	B3	608	3	6W BK	6005
					609	4	6W BK	6005
IC23B	16W GN	15	6201	B4	620A	1	2W BR	6245
Not Used				B5	Not Used			
IC23B	16W GN	5	6252	B6	6252	3	3W BK	6205
Not Used				B7	Not Used			

Drawn by: Engineering Dep. of ISACO

2015.07.07



Interconnector – Pars TU5 ECO MUX

1501052

Instrument panel				IC24B 13W GY		Front Door RH			
Part	Connector	Pin Num	Wire Num	Interconnector Pin Num		Wire Num	Pin Num	Connector	Part
Not Used				A1		Not Used			
8025A	18W BK	7	E814	A2	E814	B6	11W WI	6415	
8025A	18W BK	8							
IC20	8W WI	2							
8031	6W BK	2							
8410C	20W RD	11							
8025A	18W BK	10							
8025A	18W BK	14							
8025A	18W BK	18							
8100	3W BK	3							
8410A	8W BK	8							
IC26A	13W BK	A6							
IC20	8W WI	7							
E020A									
IC26B	13W GY	A7							
3115	2W BR	2							
8025	40W BK	24							
8025	40W BK	36							
IC23B	16W GN	14	641	A3	641	B2	11W WI	6415	
IC23B	16W GN	12	6411	A5	6411	B1	11W WI	6415	
IC23B	16W GN	13	6412	A6	6412	B3	11W WI	6415	
Not Used				A7	721	A4	11W WI	6415	
IC23B	16W GN	3	2344	B1	2344	A6	11W WI	6415	
IC23D	16W GY	1	814	B2	814	B4	11W WI	6415	
IC23B	16W GN	7	6405	B3	6405	A2	11W WI	6415	
IC23B	16W GN	8	6406	B4	6406	A1	11W WI	6415	
8445	3W BK	1	8441	B5	842	1	2W YL	8425	
8410B	8W WI	4	844						
8445	3W BK	2	8431	B6	841	2	2W YL	8425	
8410B	8W WI	3	843						
Not Used				B7	722	A5	11W WI	6415	

Rear				IC22A 16W GN		Front Door LH			
Part	Connector	Pin Num	Wire Num	Interconnector Pin Num		Wire Num	Pin Num	Connector	Part
BCMD	15W BK	B5	6021	1		6021	2	2W GY	6040
BCMD	15W BK	A1	6040	2		6040	6	18W BK	6000A
BCMD	15W BK	A3	6050	3		6050	7	18W BK	6000A
BCMA	40W BK	16	6408	4		6408	14	18W BK	6000A
BCMD	15W BK	A4	6070	5		6070	4	18W BK	6000A
BCMD	15W BK	A2	6060	6		6060	5	18W BK	6000A
BF00A	8W BK	E2	A600	7		A600	18	18W BK	6000A
E027				8	E813	A4	9W BK	6410	
4400	2W BR	2							
4730	2W WI	1							
IC32	12W WI	5							
IC33	12W WI	5							
BCMA	40W BK	4							
4310	6W BK	4							
IC6302	2W RD	2							
IC6303	2W RD	2							
3010	3W BR	2							
IC32	12W WI	8	6102A	9	A610	10	18W BK	6000A	
IC33	12W WI	8	6102B	10	6411	5	6W BK	6000B	
IC23B	16W GN	12	6411						
IC23B	16W GN	13	6412	11	6412	1	6W BK	6000B	
IC23D	16W GY	11	841	12	841	2	2W YL	8420	
IC23D	16W GY	12	842	13	842	1	2W YL	8420	
IC23B	16W GN	14	641	14	641	B2	9W BK	6410	
IC23D	16W GY	2	6120	15	6120	13	18W BK	6000A	
BCMD	15W BK	B4	6011	16	6011	1	2W GY	6040	

Drawn by: Engineering Dep. of ISACO

2015.07.07



Interconnector – Pars TU5 ECO MUX

1501052

Rear				IC22B 16W BK		Front Door LH			
Part	Connector	Pin Num	Wire Num	Interconnector Pin Num		Wire Num	Pin Num	Connector	Part
RB00B	10W WI	B5	813A	1		813	B4	9W BK	6410
IC23D	16W GY	1							
8120A	1W BK	1							
RB00D	10W WI	A1	615A	2		615	3	18W BK	6000A
RB00D	10W WI	B1	616A	3		616	2	18W BK	6000A
BCMB	15W WI	B2	6212						
IC23B	16W GN	6							
6265	2W WI	1		4		621B	2	2W BR	6240
IC32	12W WI	9							
IC33	12W WI	9							
BCMA	40W BK	7	6251	5		6251	3	3W BK	6200
BCMB	15W WI	B3	6202						
IC23B	16W GN	15							
6265	2W WI	2		6		620B	1	2W BR	6240
IC32	12W WI	7							
IC33	12W WI	7							
RB00C	10W GY	A1	617	7		617	8	18W BK	6000A
RB00C	10W GY	B1	618A	8		618	9	18W BK	6000A
BCMB	15W WI	A5	VE600						
3010	3W BR	2							
3020	3W BR	2		9		VE600	1	18W BK	6000A
IC23C	36W BK	21							
D03A		1							
IC23D	16W GY	7	V27C						
BCMB	15W WI	A7							
IC23A	16W BK	3							
IC23C	36W BK	8		10		V27C	12	18W BK	6000A
IC33	12W WI	1							
2635	6W BR	1							
2630	6W BR	6							
IC32	12W WI	1							
2633	2W BK	2	3051						
BCMA	40W BK	9		11		3051	1	2W GY	3000
BCMB	15W WI	A8							
IC23C	36W BK	9	2334	12		2334	A5	9W BK	6410
2630	6W BR	2	612						
IC23A	16W BK	15		13		612	11	18W BK	6000A
BCMA	40W BK	23		14		6407	15	18W BK	6000A
IC23B	16W GN	8	6406	15		6406	16	18W BK	6000A
						6421	A1	9W BK	6410
						6405	17	18W BK	6000A
IC23B	16W GN	7	6405	16		6431	A2	9W BK	6410

Rear				IC32 12W WI		Raer Left Door						
Part	Connector	Pin Num	Wire Num	Interconnector Pin Num		Wire Num	Pin Num	Connector	Part			
BCMB	15W WI	A7	V274	1		V274	5	6W BK	6100			
IC23A	16W BK	3										
IC23C	36W BK	8										
IC33	12W WI	1										
2635	6W BR	1										
2630	6W BR	6										
IC22B	16W BK	10										
2633	2W BK	2										
RB00C	10W GY	A3	615	2		615	2	2W GY	6130			
BCMA	40W BK	20	3071	3		3071	1	2W GY	3002			
RB00C	10W GY	A1	6121	4		6121	1	6W BK	6100			
E027			E6100	5		E813	6	6W BK	6100			
4400	2W BR	2										
4730	2W WI	1										
IC22A	16W GN	8										
IC33	12W WI	5										
BCMA	40W BK	4										
4310	6W BK	4						2	2W GY	3002		
IC6302	2W RD	2										
IC6303	2W RD	2										
3010	3W BR	2										
RB00C	10W GY	B1	6131	6		6131	2	6W BK	6100			
BCMB	15W WI	B3	6203									
IC23B	16W GN	15										
6265	2W WI	2		7		6203	1	2W BR	6250			
IC22B	16W BK	6										
IC33	12W WI	7										
IC22A	16W GN	9	6102A	8		6130	3	6W BK	6100			
BCMB	15W WI	B2	6213				4	6W BK	6100			
IC23B	16W GN	6					6213	2	2W BR	6250		
6265	2W WI	1										
IC22B	16W BK	4										
IC33	12W WI	9										
Not Used				10		Not Used						
RB00C	10W GY	B3	614	11		614	1	2W GY	6130			
Not Used				12		Not Used						

Drawn by: Engineering Dep. of ISACO

2015.07.07



Interconnector – Pars TU5 ECO MUX

1501052

Rear				IC33 12W WI	Rear Right Door			
Part	Connector	Pin Num	Wire Num	Interconnector Pin Num	Wire Num	Pin Num	Connector	Part
BCMB	15W WI	A7	V273	1	V274	5	6W BK	6105
IC23C	36W BK	8						
IC22B	16W BK	10						
IC32	12W WI	1						
2635	6W BR	1						
2630	6W BR	6						
IC23A	16W BK	3						
2633	2W BK	2						
RB00D	10W WI	B3						
BCMA	40W BK	19						
RB00D	10W WI	A1	619	2	615	2	2W GY	6135
			3081	3	3071	1	2W GY	3003
			6161	4	6121	1	6W BK	6105
	E027		E6105	5	E813	6	6W BK	6105
4400	2W BR	2						
4730	2W WI	1						
IC22A	16W GN	8						
IC32	12W WI	5						
BCMA	40W BK	4				2	2W GY	3003
4310	6W BK	4						
IC6302	2W RD	2						
IC6303	2W RD	2						
3010	3W BR	3						
RB00D	10W WI	B1	6171	6	6131	2	6W BK	6105
BCMB	15W WI	B3	6204	7	6203	1	2W BR	6255
IC22B	16W BK	6						
6265	2W WI	2						
IC23B	16W GN	15						
IC32	12W WI	7						
IC22A	16W GN	9	6102B	8	6130	3	6W BK	6105
						4	6W BK	6105
BCMB	15W WI	B2	6214	9	6213	2	2W BR	6255
IC22B	16W BK	4						
6265	2W WI	1						
IC23B	16W GN	6						
IC32	12W WI	9						
Not Used				10	Not Used			
RB00D	10W WI	A3	618	11	614	1	2W GY	6135
Not Used				12	Not Used			

Rear				IC220 8W WI	Rear Bumper(Crouse)			
Part	Connector	Pin Num	Wire Num	Interconnector Pin Num	Wire Num	Pin Num	Connector	Part
BCMB	15W WI	A4	2202	1	226	2	4W BK	2234
2635	6W BR	4				2	4W BK	2230
2630	6W BR	3						
IC23C	36W BK	31						
	E026G		E754	2	E223	4	4W BK	2234
2630	6W BR	1				1	4W BK	2230
2633	2W BK	1						
3020	3W BR	3				4	4W BK	2230
3100	2W BR	2						
2110	2W WI	1						
2111	2W BR	1						
IC23C	36W BK	23				2207	3	227
Not Used				4	Not Used			
Not Used				5	Not Used			
Not Used				6	Not Used			
Not Used				7	Not Used			
Not Used				8	Not Used			

Drawn by: Engineering Dep. of ISACO

2015.07.07



Interconnector – Pars TU5 ECO MUX

1501052

Instrument panel				IC26A 13W BK		Air Condition								
Part	Connector	Pin Num	Wire Num	Interconnector Pin Num		Wire Num	Pin Num	Connector	Part					
IC23A	16W BK	8	803A	A1	8032	1	5W	8048A						
						5	5W	8048A						
IC26A	13W BK	B7				1	5W	8048B						
8031	6W BK	3												
Not Used				A2		Not Used								
8025	40W GY	33	8048	A3		8048	4	7W BK	8065					
8025	40W GY	9	8049	A5		8049	5	7W BK	8065					
8025A	18W BK	7	E805	A6	E804	2	5W		8048A					
8025A	18W BK	8												
IC20	8W WI	2												
8031	6W BK	2												
8410C	20W RD	11												
8025A	18W BK	10												
8025A	18W BK	14				1	3W BK	8045						
8025A	18W BK	18												
8100	3W BK	3												
8410A	8W BK	8												
IC20	8W WI	7												
IC26B	13W GY	A7												
IC24B	13W GY	A2				E805	3	5W	8048B					
E020A														
3115	2W BR	2												
8025	40W GY	24												
8025	40W GY	36												
8033	2W BK	2												
8031	6W BK	6	E804	A7	E803	2	2W BK	8006						
8025	40W GY	34												
8025	40W GY	1							8040	B1	8040	1	7W BK	8040
8025	40W GY	21							8041	B2	8041	2	7W BK	8040
8025	40W GY	32							8042	B3	8042	4	7W BK	8040
8025	40W GY	8							8043	B4	8043	5	7W BK	8040
8025	40W GY	29	8044	B5	8044	6	7W BK	8040						
						6	7W BK	8065						
8025	40W GY	28	8045	B6	8045	7	7W BK	8040						
						7	7W BK	8065						
IC23A	16W BK	8	803B	B7	Not Used									
IC26A	13W BK	A1												
8031	6W BK	3												

Instrument panel				IC26B 13W GY		Air Condition			
Part	Connector	Pin Num	Wire Num	Interconnector Pin Num		Wire Num	Pin Num	Connector	Part
8025	40W GY	2	8026	A1		8026	5	7W BK	8067
8025	40W GY	22	8027	A2		8027	4	7W BK	8067
8025	40W GY	23	8028	A3		8028	2	7W BK	8067
8025	40W GY	3	8046	A5		8046	2	7W BK	8065
8025	40W GY	4	8047	A6		8047	1	7W BK	8065
8025A	18W BK	7	E806	A7	Not Used				
8025A	18W BK	8							
IC20	8W WI	2							
8031	6W BK	2							
8410C	20W RD	11							
8025A	18W BK	10							
8025A	18W BK	14							
8025A	18W BK	18							
8100	3W BK	3							
8410A	8W BK	8							
IC20	8W WI	7							
IC26A	13W BK	A6							
IC24B	13W GY	A2							
E020A									
3115	2W BR	2							
8025	40W GY	24	8038B	B1	Not Used				
8025	40W GY	36							
IC23A	16W BK	7							
8025	40W BK	38	8039	B2	8039	2	5W	8048B	
8025	40W GY	13	8021	B3	8021	1	2W BK	8006	
8025	40W GY	15	8022	B4	8022	3	5W	8048A	
						1	2W	8050	
8025	40W GY	16	8023	B5	8023	3	3W BK	8045	
						2	2W	8050	
8025	40W GY	17	8024	B6	8024	2	3W BK	8045	
						5	5W	8048B	
Not Used				B7		Not Used			

Drawn by: Engineering Dep. of ISACO

2015.07.07



Interconnector – Pars TU5 ECO MUX

1501052

Instrument panel				IC20 8W WI		Power Steering			
Part	Connector	Pin Num	Wire Num	Interconnector Pin Num		Wire Num	Pin Num	Connector	Part
8410C	20W RD	8	C8	1		C8	5	8W WI	8413A
8025A	18W BK	7							
8025A	18W BK	8							
IC20	8W WI	7							
8031	6W BK	2							
8410C	20W RD	11							
8025A	18W BK	10							
8025A	18W BK	14							
8025A	18W BK	18							
8100	3W BK	3							
8410A	8W BK	8							
IC26B	13W GY	A7							
IC26A	13W BK	A6							
IC24B	13W GY	A2							
E020A									
3115	2W BR	2							
8025	40W GY	24							
8025	40W GY	36							
IC23B	16W GN	11	252	3	252	3	8W WI	CT00	
Not Used				4		Not Used			
Not Used				5		Not Used			
8410A	8W BK	6	V19R	6	V841	2	8W WI	8413A	
8025A	18W BK	6							
8025	40W GY	35							
3053	1W BK	1							
IC24A	13W BK	A3							
IC23A	16W BK	3							
8025A	18W BK	7							
8025A	18W BK	8	E842	7	E841	3	8W WI	8413A	
IC20	8W WI	2							
8031	6W BK	2							
8410C	20W RD	11							
8025A	18W BK	10							
IC26B	13W GY	A7							
8025A	18W BK	14							
8025A	18W BK	18							
8100	3W BK	3							
8410A	8W BK	8							
IC26A	13W BK	A6							
IC24B	13W GY	2							
E020A									
3115	2W BR	2							
8025	40W GY	24							
8025	40W GY	36							
Not Used				8		Not Used			

Front Panel				IC01 16W BK		Main			
Part	Connector	Pin Num	Wire Num	Interconnector Pin Num		Wire Num	Pin Num	Connector	Part
IC01	16W BK	2	155A	1	155A	155A	2	16W BK	IC01
1510B	2W BK	1					1	10W BK	IC02B
							B5	10W GY	RB003
IC01	16W BK	1	155B	2	155B	B4	10W WI	RB004	
1510B	2W BK	1				1	16W BK	IC01	
						B5	10W GY	RB003	
8032	2W BR	1	832	3	832	20	36W BK	IC23C	
2320	2W BR	1	2331	4	2333	9	36W BK	IC23C	
2610A	3W BK	C	PC3	5	PC3	1	2W BR	2340	
2610A	3W BK	R	PR3	6	PR3	B3	15W WI	FCMB	
IC01	16W BK	8	E15A1	7	E15A	B3	10W WI	RB004	
1510A	2W BK	2							
IC01	16W BK	7	E15A2	8	E15B	B3	10W WI	RB004	
1510A	2W BK	2							
2620	2W WI	1	V091	9	V275	8	36W BK	IC23C	
2325	2W BR	1	2341	10	2343	10	36W BK	IC23C	
2520A	2W WI	1	250	11	250	1	2W BR	2345	
2520B	2W WI	1							
2670	2W BU	1	2673	12	2673	B3	10W BK	RB001	
2675	2W BU	1							
IC01	16W BK	14	154A	13	154A	A5	10W GY	RB003	
1510A	2W BK	1							
IC01	16W BK	13	154B	14	154B	A5	10W GY	RB003	
1510A	2W BK	1							
2615A	3W BK	C	PC4	15	PC4	B5	15W BK	FCMA	
2615A	3W BK	R	PR4	16	PR4	B4	15W BK	FCMA	

Drawn by: Engineering Dep. of ISACO

2015.07.07



Interconnector – Pars TU5 ECO MUX

1501052

Engine				IC02A	10W	GY	Main			
Part	Connector	Pin Num	Wire Num	Interconnector Pin Num		Wire Num	Pin Num	Connector	Part	
1320	90W BK	B29	8090	1	C341	4	8W BK	8208		
8007	4W BR	1				1	16W BK	C001		
8007	4W BR	4				9	18W WI	ICN		
1010A	1W	1				E3	8W BK	BF00D		
1304	10W BK	B3	121	2	1086	E4	8W BK	BF00D		
4110	2W GY	2	410	3	121	7	36W BK	IC23C		
4025	3W GY	1	403	4	410	A7	15W BK	FCMA		
2200	2W GY	2	220	5	403	22	36W BK	IC23C		
1020A	2W BK	1	1070	6	220	A6	15W BK	FCMA		
8020	2W YL	1	8079	7	1070	A9	15W WI	FCMB		
1320	90W BK	A9	809	8	8079	B3	15W BK	FCMA		
1320	90W BK	A10	8091	9	809	A2	10W GY	RB003		
1320	90W BK	A10	8091	10	8091	B2	10W GY	RB003		

Engine				IC02B	10W	BK	Main			
Part	Connector	Pin Num	Wire Num	Interconnector Pin Num		Wire Num	Pin Num	Connector	Part	
1320	90W BK	A45	1510	1	1510	1510	1	16W BK	IC01	
							2	16W BK	IC01	
							B5	10W GY	RB003	
							B4	10W WI	RB004	
1320	90W BK	B56	1411	2	1411	7	16W BK	C001		
1320	90W BK	B57	9019C	3	9019C	6	8W BK	8208		
						14	16W BK	C001		
						12	36W BK	IC23C		
						2	38W BK	7020		
1320	90W BK	B88	9020C	4	9020C	5	8W BK	8208		
						6	16W BK	C001		
						11	36W BK	IC23C		
						14	38W BK	7020		
Not Used				5	1810	34	36W BK	IC23C		
1320	90W BK	B51	1628	6	1628	17	38W BK	7020		
1320	90W BK	B46	430	7	430	13	36W BK	IC23C		
1320	90W BK	B82	431	8	431	14	36W BK	IC23C		
Not Used				9	183	26	36W BK	IC23C		
Not Used				10	184	15	36W BK	IC23C		

Brake Wear Warning				IC03A	2W	WI	Main			
Part	Connector	Pin Num	Wire Num	Interconnector Pin Num		Wire Num	Pin Num	Connector	Part	
4431		1	445	1		446	1	2W WI	IC03B	
E009		M44		2	E44A	E44A	2	E006		
							2	2W BK	5100	
							2	2W BR	2345	



Interconnector – Pars TU5 ECO MUX

1501052

Brake Wear Warning				IC03B 2W WI	Main			
Part	Connector	Pin Num	Wire Num	Interconnector Pin Num	Wire Num	Pin Num	Connector	Part
4430		1	445	1	445	A9	15W BK	FCMA
					446	1	2W WI	IC03A
E009			M44	2	E44B	E005		
						2	2W BR	2340
						2	2W BK	4410
						B4	15W WI	FCMB
						A4	10W GY	RB002

Rear				IC6302 2W RD	Seat								
Part	Connector	Pin Num	Wire Num	Interconnector Pin Num	Wire Num	Pin Num	Connector	Part					
BF00A	10W BK	E4	A211A	1	K20	3	5W BR	6340					
E027				2	E63B	2	5W BR	6340					
4400	2W BR	2											
4730	2W WI	1											
IC22A	16W GN	8											
IC32	12W WI	5											
BCMA	40W BK	4											
4310	6W BK	4											
3065	2W BR	2											
IC33	12W WI	5											
IC6303	2W RD	2											
3010	3W BR	3											

Rear				IC6303 2W RD	Seat								
Part	Connector	Pin Num	Wire Num	Interconnector Pin Num	Wire Num	Pin Num	Connector	Part					
BF00A	10W BK	E4	A212B	1	K20	3	5W BR	6345					
E027				2	E63B	2	5W BR	6345					
4400	2W BR	2											
4730	2W WI	1											
IC22A	16W GN	8											
IC32	12W WI	5											
BCMA	40W BK	4											
4310	6W BK	4											
3065	2W BR	2											
IC6302	2W RD	2											
IC33	12W WI	5											
3010	3W BR	3											

Engine				IC022 6W BK	Injector						
Part	Connector	Pin Num	Wire Num	Interconnector Pin Num	Wire Num	Pin Num	Connector	Part			
1320	90W BK	B59	1321	1	1321	1	2W BK	1331			
1320	90W BK	B89	1322	2	1322	1	2W BK	1332			
1350B	4W BK	3	1200	3	1320	2	2W BK	1331			
1135	6W BK	2				2	2W BK	1332			
1215	2W BR	2				2	2W BK	1333			
1350A	4W GY	3				2	2W BK	1334			
1320	90W BK	A66									
1304	10W BK	A5									
Not Used				4	Not Used						
1320	90W BK	B90	1323	5	1323	1	2W BK	1333			
1320	90W BK	B60	1324	6	1324	1	2W BK	1334			

Drawn by: Engineering Dep. of ISACO

2015.07.07